



CSR-6.2L & CSR-6.4L CONEKT[®] MOBILE-READY CONTACTLESS SMARTCARD READER AND KEYPAD



CSR-6.2L mounts to mullion



CSR-6.4L mounts to single-gang wall switch box

Conekt Mobile Smartphone Access Control Solution



Frequency: 13.56 MHz and 2.4 GHz

Read Range:

Physical Credentials: Up to 2 inches (51 mm)

Mobile Credentials: Up to 15 feet (4.6 m)



Bluetooth Low Energy

Supports Conekt Smartphone Mobile Access Credentials



Optimized for MIFARE[®] DESFire[®] EV1 & EV2

Integrated High-Security Contactless Smartcard Support



MAXSecure[™]

Unique Security Feature



ValidID[™]

Fraudulent Data Detection Solution



Warranty

Farpointe Lifetime Warranty



Wiegand, ABA Track II Magnetic Stripe or OSDP*

Output Interface



Mullion Mount (CSR-6.2L)

Metal Door, Window Frames & Flat Surfaces



U.S. Single-Gang Wall-Box Mount (CSR-6.4L)

Box & Flat Surfaces

*OSDP readers are independent models and need to be appended with the suffix "-OSDP" when ordering (Example: CSR-6.2L-OSDP).

CSR-6.2L & CSR-6.4L CONEKT® MOBILE-READY CONTACTLESS SMARTCARD READER AND KEYPAD

Conekt comprises Farpointe Data’s contactless smartcard reader solution with mobile access support. Based upon the proven LEGIC® contactless digital radio frequency identification (RFID) platform, Conekt readers interface with a wide range of electronic access control systems by complying with either the legacy Wiegand and ABA Track II magnetic stripe formats, or the latest bi-directional Open Supervised Device Protocol (OSDP). They offer value-add features such as MAXSecure™ and ValidID™, and support both sector and card serial number (CSN) reads. In addition to traditional contactless smartcard access credentials, such as clamshell cards and key tags, the platform also offers the option of mobile access credentials loaded on Bluetooth Low Energy (BLE)-enabled smartphones. This allows the smartphone to function as a contactless electronic access control credential. Conekt access credentials, both traditional and mobile, can be ordered programmed to various formats in exact number sequence required.

Specifications	CSR-6.2L & CSR-6.4L Conekt Mobile-Ready Contactless Smartcard Reader and Keypad
Models	CSR-6.2L Mullion-Mount Mobile-Ready Contactless Smartcard Reader and Keypad CSR-6.4L Single-Gang Wall Switch Box Mount Mobile-Ready Contactless Smartcard Reader and Keypad
Technology ¹	Contactless smartcard and Bluetooth Low Energy (BLE)
Frequency	13.56 MHz (contactless smartcard) and 2.4 GHz (BLE)
Mounting ²	CSR-6.2L: Mullions, including metal door and window frames, as well as flat surfaces CSR-6.4L: Single-gang wall box, as well as flat surfaces
Dimensions	CSR-6.2L: 1.78" W × 6.1" H × 0.91" D (45 mm × 155 mm × 23 mm) CSR-6.4L: 3" W × 4.6" H × 0.75" D (76 mm × 117 mm × 19 mm)
OEM Label Area	0.9" W × 0.35" H (22.86 mm × 8.89 mm) with corner radius of 0.06" (1.5 mm)
Certifications	FCC, ICC, CE
IP Code ³	IP67
Voltage ⁴	+8 – 14 VDC
Current Draw	175 mA typical @ 12 VDC
Read Range ⁵	Physical Credentials: Up to 2 inches (51 mm) Mobile Credentials: Up to 15 feet (4.6 m)
Cabling ⁶	24 AWG minimum, multiconductor stranded with an overall foil shield
Interface	Wiegand (26-bit and custom formats), ABA Track II magnetic stripe (clock and data) or OSDP ⁷
Operating Temperature	–40° F to 149° F (–40° C to +65° C)
Color Options	A black snap-on cover included standard
Audio Tone	Beeper included standard
Indoor & Outdoor Installation	Electronics sealed in weather- and tamper-resistant epoxy potting
Warranty	Limited lifetime warranty
LED	Four-state standard (red, green, amber, and off)
Keypad Output	Either Wiegand ⁸ or OSDP ⁷
Technologies Supported	Interoperable with CSN ⁹ (may include ISO 14443 compliant credentials and MIFARE® Classic 1k & 4k, MIFARE® DESFire® EV1 & EV2, MIFARE UltraLight® and MIFARE Plus®), and Sector (may include Delta Card Sector ¹⁰ , such as MIFARE® Classic 1k & 4k, MIFARE® DESFire® EV1 & EV2, as well as FIPS201 [PIV Type A], TWIC, and CAC credentials), as well as Conekt Mobile Access Credentials. ¹¹

NOTES:

- 1 Optimized for use with devices supporting BLE version 4.2 or newer.
- 2 Spacer included standard for installations on metal. Depending on environment, additional spacing may be required.
- 3 Independently tested and verified by Intertek.
- 4 Linear power supplies are recommended for best operation.
- 5 Using DC1-1 Delta Clamshell Contactless Smartcard with 12 VDC at the reader. Other credentials may be less. Read ranges are further subject to the type of smartphone, as well as the manner in which it is used, covers or external batteries affixed, as well as the installation and its environment.
- 6 For example, Belden 9535 or similar, supporting the five conductors comprising the physical layer of the Wiegand interface (power, ground, data 0, data 1, and/or beeper and LED). Alternatively, Belden 9539 or similar, for all reader functions. Shielded, twisted pair (Belden 8723 or similar) for OSDP. Contact your access control system manufacturer for their specific requirements.
- 7 OSDP readers are independent models and need to be appended with the suffix "-OSDP" when ordering (Example: CSR-6.2L-OSDP).
- 8 8-Bit Burst or 26-bit Wiegand standard. For 4-Bit Burst and other options, please contact Farpointe.
- 9 CSN = Card Serial Number.
- 10 Examples include, but are not limited to, DC1-1, DM1-3, and DK1-3.
- 11 Conekt Mobile Access Credentials are intended to be supported by the current and preceding versions of Apple® iOS and standard compliant Google Android™ mobile operating software (OS). Custom OS variants may result in a loss of functionality.

Patent Pending

Farpointe Data reserves the right to change specifications without notice.

© 2020 Farpointe Data, Inc. All rights reserved. Farpointe Data®, Pyramid Series Proximity®, Delta®, Ranger®, and CONEKT® are the registered U.S. trademarks of Farpointe Data, Inc. LEGIC is a registered trademark of LEGIC Identsystems Ltd. MIFARE®, MIFARE DESFire®, MIFARE UltraLight®, and MIFARE Plus are registered trademarks of NXP B.V. All other trademarks are the property of their respective owners.

Farpointe Data, Inc.
2195 Zanker Road
San Jose, CA 95131 USA
Office: +1-408-731-8700
Fax: +1-408-731-8705
support@farpointedata.com

